A CONFIGURABLE ARRANGEMENT OF MULTIPLE TRANSMITTERS AND MULTIPLE RECEIVERS FOR THE PERFORMANCE OF REMOTE CONVENIENCE FUNCTIONS

Technical Field

5   The present invention relates to remote

convenience systems, and is particularly directed to

arrangements configured to support communications

between a plurality of portable transceivers and a

plurality of device-based transceivers.

Background of the Invention

10

Remote convenience systems are known in the art.

Such remote convenience systems permit remote control

of certain functions. One type of remote convenience

system is for remotely controlling vehicle functions.

15   Other example types of remote convenience systems

include garage door opener systems and entry light

activation systems.

A CONFIGURABLE ARRANGEMENT OF MULTIPLE TRANSMITTERS AND MULTIPLE RECEIVERS FOR THE PERFORMANCE OF REMOTE CONVENIENCE FUNCTIONS

Technical Field

5   The present invention relates to remote convenience systems, and is particularly directed to arrangements configured to support communications between a plurality of portable transceivers and a plurality of device-based transceivers.

10   ### Background of the Invention

Remote convenience systems are known in the art. Such remote convenience systems permit remote control of certain functions. One type of remote convenience system is for remotely controlling vehicle functions.

15   Other example types of remote convenience systems include garage door opener systems and entry light activation systems.

Focusing now on the remote convenience vehicle

systems, examples of remotely controlled functions

include locking and unlocking of one or more vehicle

doors. A remote convenience vehicle system that

5   permits remote locking and unlocking functions is

commonly referred to as a remote keyless entry system.

Such remote convenience vehicle systems may

provide for control of other vehicle functions. For

example, a remote vehicle locator function may be

10   provided. The vehicle locator function causes the

vehicle horn to emit a horn chirp and/or the headlights

of the vehicle to flash "ON". This allows a person to

quickly locate their vehicle within a crowded parking

lot.

15   Known remote convenience vehicle systems include a

receiver unit mounted in an associated vehicle and at

least one portable, hand-held transmitter unit located

remote from the receiver unit. Each transmitter unit

is provided with one or more manually actuatable

20   pushbutton switches. Each pushbutton switch is

associated with a remote control vehicle function to be

performed. The transmitter unit includes circuitry

that responds to the actuation of each pushbutton

switch to transmit a message in the form of a digital signal.

As the sophistication of vehicles has increased, the number and complexity of vehicle systems has increased. Following this increase in number and complexity of vehicle systems, there has been a movement toward an increase in the number of systems and the number of tasks that are to be remotely controlled.

Focusing now on remote convenience functions that are part of non-vehicle systems (e.g., garage door opener systems and entry light activation systems), there has also been an increase in the number of devices and tasks that are to be remotely controlled. Thus, it is common for a person to have a portable transmitter unit associated with a remote convenience vehicle system, a portable transmitter unit associated with a garage door opener system, and a portable transmitter unit associated with an entry light activation system.

It is common for a person to have authorized access to a plurality of vehicles. Accordingly, the person may have a plurality of portable transmitter

units, each unit being associated with a different

vehicle.

Summary of the Invention

In accordance with one aspect, the present

5   invention provides an arrangement for remotely

controlling convenience functions at a plurality of

devices. Each device-based receiver means in a

plurality of device-based receiver means, receives a

remote convenience function request signal and conveys

10   a remote convenience function request message to a

device operations system for use in performing a

remotely requested convenience function. Each portable

transmitter means in a plurality of portable

transmitter means, is configurable to be compatible

15   with any of the plurality of receiver means for

outputting a remote convenience function request signal

to cause remote control performance of a function at

the respective device.

In accordance with another aspect, the present

20   invention provides a convenience function request

message for transmission by one of a plurality of

portable transmitters to perform a remote convenience

function on a device in an arrangement having a

plurality of devices. The request message includes

portable transmitter configuration information and
device configuration information.

In accordance with another aspect, the present
invention provides configuration information stored in

5   the memory of a portable transmitter. The

configuration information includes a portable
transmitter serial number and a transmitter entity
table.

In accordance with another aspect, the present

10   invention provides configuration information stored in
the memory of a device-based receiver. The
configuration information includes a device
identification number, a communication channel number,
and a receiver entity table.

15   In accordance with another aspect, the present
invention provides a method for remotely controlling
convenience functions on one of a plurality of devices
using one of a plurality of portable transmitters in a
configured arrangement. Input is received at a

20   transmitter from an operator designating a device-based
receiver from a plurality of device-based receivers for
which the transmitter is to be compatible in the
configured arrangement. A subset of transmitter
configuration information is retrieved from transmitter

memory according to the input received from the operator. The transmitter configuration information allows the transmitter to have compatibility with a plurality of receivers.

5   Input is received at the transmitter from the operator. The input received is indicative of a remote convenience function request. A remote convenience function request message is generated at the transmitter. The portion of the subset of the

10   transmitter configuration information that corresponds to the receiver selected by the operator is used in the convenience function request message. The remote convenience function request message is encrypted at the transmitter. The encrypted remote convenience

15   function request message is transmitted from the transmitter.

The remote convenience function request message is received at the receiver. The validity of the remote convenience function request message is determined

20   according to the receiver configuration information stored in receiver memory. The receiver configuration information allows the receiver to have compatibility with the plurality of transmitters.

The valid remote convenience function request
message is decrypted at the receiver that determined
that it received a valid remote convenience function
request message. The remote convenience function

5   request contained within the received convenience
function request message is conveyed to the device
operations system of the device whose receiver
determined that it received a valid remote convenience
function request message.

Brief Description of the Drawings

The foregoing and other features and advantages of
the present invention will become apparent to those
skilled in the art to which the present invention
relates upon reading the following description with

15   reference to the accompanying drawings, wherein:

Fig. 1 is a function block diagram of an
arrangement for remote control of convenience functions
featuring a plurality of portable transceivers and a
plurality of devices;

20   Fig. 2 is a detailed function block diagram of one
of the plurality of portable transceivers illustrated
in Fig. 1;

Fig. 3 is a function block diagram of one of the plurality of devices illustrated in Fig. 1 with detailed view of the device-based transceiver;

Fig. 4 is an illustration of the configuration

5   information stored in the memory of a portable transceiver;

Fig. 5 is an illustration of the configuration information stored in the memory of a device-based transceiver;

10   Fig. 6 is a flow chart for a process performed by a portable transceiver;

Fig. 7 is a flow chart for a process performed by a device-based transceiver;

Fig. 8 is an illustration of the configuration

15   information stored in the memory of the portable and device-based transceivers depicted in Fig. 1.

Description of Example Embodiment

An arrangement 10 for remote control of convenience functions, in accordance with the present

20   invention, is schematically shown in Fig. 1.   For ease of illustration and discussion, similar components of the arrangement 10 are identified by identical reference numerals, but with different letter suffixes.

It is to be appreciated that the similar components may or may not have identical structures or configurations.

The embodiment of the arrangement 10 depicted in Fig. 1 includes portable hand-held transceiver units 20A, 20B, and 20C (hereinafter referred to as "the portable transceivers") and device-based transceiver units 30X and 30Y (hereinafter referred to as "the device-based transceivers"). The device-based transceivers 30X and 30Y are located at devices 35X and 35Y, respectively. In the presented embodiment, the devices 35X and 35Y are vehicles, and authorized users (e.g., vehicle owners) of the vehicles hold the portable transceivers 20A-20C.

It is to be appreciated that the presented embodiment is an example and that modifications are possible. Possible modifications include a different number of portable and/or device-based transceivers. As another possibility, the device-based transceivers may be associated with non-vehicles devices. Such devices may be buildings (e.g., houses) or other products that would be associated with the use of remote convenience functions. Also, the arrangement 10 may be configured so that a combination of device types

(e.g., vehicles and buildings) coexists in the same arrangement.

At each device (e.g., 35X) is a device operations system (e.g., 38X) that is remotely controlled via at least one of the portable transceivers 20A-20C. Depending on the type of device, the remotely-controlled function may be associated with door locks, trunk lids, engine ignitions, windows, headlights, horn, seat controls, building lights, and garage doors. Specifically, examples of remotely-controlled convenience functions include, for example, locking and unlocking doors, opening and closing windows, and turning lights ON and OFF.

Each portable transceiver (e.g., 20A), is capable of communicating (transmitting and receiving) with any device-based transceiver (e.g., 30X) from a remote location. Each device-based transceiver (e.g., 30X) is capable of communicating (transmitting and receiving) with any portable transceiver, (e.g., 20A). Specifically, each portable transceiver (e.g., 20A) is operable by a user to communicate a convenience function request to an operator-selected device (e.g., 35X) so that remote control performance of at least one convenience function (e.g., unlock doors) is

achieved at the operator-selected device. In the

arrangement 10 shown in Fig. 1, the user of one of the

portable transceivers (e.g., 20A) selects either

device 35X or device 35Y for performance of a

5   convenience function thereat. The device-based

transceiver (e.g., 30X), whose associated device was

selected by the user to perform a convenience function,

can transmit information feedback, and the like, to the

portable transceiver that requested the convenience

10   function. Thus, two-way communications exists.

Also, the arrangement 10 allows a plurality of

users to control a plurality of devices. The

arrangement 10 illustrated in Fig. 1 is configured so

that each portable transceiver (e.g., 20A) can remotely

15   control the respective device operations systems 38X

and 38Y of devices 35X and 35Y through communications

with each device's respective device-based

transceiver, 30X, 30Y. Thus, any portable

transceiver 20A-20C can control any device 35X, 35Y

20   in the arrangement 10 of Fig. 1.

Further, the arrangement 10 may be configured so

that a particular portable transceiver (e.g., 20A) can

remotely control only some (e.g., 35X) of the devices.

For example, the arrangement 10 illustrated in Fig. 1

may be configured to allow portable transceiver 20A to control device 35X, portable transceiver 20B to control device 35Y, and portable transceiver 20C to control devices 35X and 35Y. Such configuration is termed

5 "mixing-and-matching". Thus, depending on the configuration of the arrangement 10, a given portable transceiver may control the functions on some or all of the devices in an arrangement.

Consider, for the moment, portable transceiver 20A

10 of the arrangement 10 shown in Fig. 1. The portable transceiver 20A includes a controller 42A that generates/assembles a "packet" of information to be transmitted to the device-based transceivers 30X, 30Y. The packet of information includes a convenience

15 function request. Radio frequency (RF) transceive circuitry 44A is operatively connected 45A to controller 42A to receive the message packet that is to be transmitted. The RF transceive circuitry 44A is operatively connected 47A to an antenna 48A. In

20 response to an electrical stimulus that conveys the message packet, the antenna 48A broadcasts an electromagnetic signal (e.g., 53 or 53') that conveys the message packet. For ease of illustration and discussion, electromagnetic signals bearing the same

message packet from a portable transceiver are referred
to by a like number with the absence or presence of a
prime (') suffix. Similarly, electromagnetic
signals 55, 55' originate from the portable
transceiver 20B, and electromagnetic signals 57, 57'
originate from the portable transceiver 20C.

In one example, transmitted signals 53, 53', 55,
55', 57, 57' are pulse-width-modulated (PWM) signals
that have a radio frequency (RF) carrier frequency. It
is to be appreciated that other signal types (e.g.,
frequency modulation, frequency shift key, or the like)
may be used without deviating from the present
invention.

Turning now to the device-based transceiver
(e.g., 30X), an antenna 62X receives the transmitted
signal (e.g., 53) broadcast from a portable transceiver
(e.g., 20A). For this discussion, the device-based
transceiver 30X could have received a different signal
(e.g., 55) from another portable transceiver
(e.g., 20B). Antenna 62X, which is operatively
connected 63X to RF transceive circuitry 64X, outputs
an electrical signal that conveys the message packet to
the RF transceive circuitry 64X. In turn, the RF
transceive circuitry 64X communicates the message

packet, via a connection 67X, to a controller 68X. As

part of the functions performed by the controller 68X,

the controller determines if the broadcast signal 53 is

intended for the associated device 35X and outputs

5   appropriate control commands to the device operations

system 38X.

As noted above, each broadcast signal, 53, 53',

55, 55', 57, 57', illustrated in Fig. 1, bears a

convenience function message intended to cause

10   performance by a device operations system selected by

an operator. When a portable transceiver transmits a

broadcast signal, all of the device-based transceivers

in the arrangement may receive the transmitted

broadcast signal. Each device-based transceiver, 30X,

15   30Y, decodes the broadcast signal and determines if the

convenience function message is intended for its own

respective device operations system 38X, 38Y.

If the convenience function message is determined

to not be intended for a device's operations system,

20   then the device-based transceiver goes into sleep mode

to await another broadcast signal from a portable

transceiver. If the convenience function message is

determined to be intended for a device's operations

system, then the requested convenience function is

performed.   In one example, a status response message

is transmitted by the device-based transceiver to the

portable transceiver that requested the convenience

function.   Depicted in Fig. 1 are signals 71, 72, 73,

5   75, 76, 77 which bear the status response messages

transmitted from devices 35X, 35Y.

Preferably, the transmitted signals 71, 72, 73,

75, 76, 77 are pulse-width-modulated (PWM) signals that

have a radio frequency (RF) carrier frequency.   It is

10   to be appreciated that other signal types

(e.g., frequency modulation, frequency shift key or

the like) may be used without deviating from the

present invention.

It is to be appreciated that each portable

15   transceiver can control a plurality of types of

remotely controlled devices (e.g., vehicles, buildings,

etc.) as well as a plurality of functions at each

device.   Each portable transceiver is configured to

provide a great amount of control via its single unit

20   without the unit having undue bulk or size.

The portable transceiver 20A illustrated in Fig. 2

in greater detail is an example of the configuration of

the portable transceivers 20A, 20B, and 20C (Fig 1).

It is to be appreciated that the portable transceivers 20B and 20C may have similar structure.

The portable transceiver 20A (Fig. 2) includes a plurality of manually actuatable pushbutton selector switches. In the example there are five pushbutton switches 91A-95A. The pushbutton switches 91A-95A are identified by indicia labels "lock", "unlock", "TRUNK" or "TR", "panic", and "mode". It is to be appreciated that the indicia used within the example are chosen merely to aid the operator in identifying and remembering various pushbutton switches. It is to be appreciated that different indicia may be utilized.

The first-fourth pushbutton switches 91A-94A (i.e., identified by lock, unlock, TR, and panic) are associated with requests for remote convenience function performance. Actuation of the fifth (mode) pushbutton switch 95A on portable transceiver 20A signals the controller 42A to change between the modes in which convenience functions at different devices are to be controlled. Selecting a mode on a portable transceiver is, in effect, selecting a device to control. Each actuation of the fifth (mode) pushbutton switch 95A toggles through the devices configured on a particular portable transceiver. The number of devices

an operator is able to toggle through is dependent on

the configuration of the arrangement in general and the

number of devices configured on his or her portable

transceiver in particular.

5   For example, the arrangement 10 illustrated in

Fig. 1 may be configured to allow portable

transceiver 20A to control devices 35X and 35Y.

Thus, portable transceiver 20A would be able to toggle

between devices 35X and 35Y. It is to be appreciated

10   that the first-fourth pushbutton switches 91A-94A may

have their associated functions changed depending on

the type of device that is selected with the fifth

(mode) pushbutton switch 95A.

In order for the operator of the portable

15   transceiver 20A (Fig. 2) to know the convenience

functions currently assigned to the pushbutton

switches 91A-94A, a display 82A is provided on the

portable transceiver 20A. The display 82A can also

provide an operator information about the current mode

20   of the portable transceiver 20A and certain response or

acknowledgement information provided from a device-

based transceiver (e.g., 30X, Fig. 1). In one example,

the display 82A (Fig. 2) is a liquid crystal display

capable of displaying alphanumeric characters and/or

other symbology.   Designated alphanumeric character

phrases and symbols can be used to denote certain types

of information.   For example, icons can be used to

denote the device mode of the portable transceiver 20A

5   while alphanumeric character phrases can be used to

indicate the current first and second pushbutton switch

assignments as well as any response/acknowledgements

received from device-based transceivers.   Other

character/symbol arrangements may be used to denote the

10   different types of information.   Structurally, as shown

in Fig. 2, the display 82A is operatively connected 43A

to the controller 42A.

Each device (e.g., 35X, Fig. 1) can provide

response or feedback to the portable transceiver 20A.

15   The response or feedback can be associated with the

performance of a remote convenience function.   For

example, if the remotely requested function is to lock

a vehicle's doors, the device-based transceiver located

at the vehicle may respond with an acknowledgement that

20   the vehicle doors have been locked as requested.

Similarly, if the requested function is to turn OFF the

light at a building, the response signal from the

device-based transceiver located at the building may be

an acknowledgement that the light has indeed been turned OFF.

Turning attention to the controller 42A of the portable transceiver 20A illustrated in Fig. 2, the controller has at least three portions. A process portion 112A controls the controller 42A and processes information. A memory portion 114A stores information. The memory portion 114A is preferably an electrically erasable programmable read-only memory (EEPROM), but can be any non-volatile memory that can be programmed by the circuitry within the portable transceiver. An encrypt portion 116A encrypts messages for secure communications to devices (e.g., 35X, Fig. 1). It is to be appreciated that the functions performed within the blocks of the controller part of the diagram shown in Fig. 2 may be accomplished by discrete hard-wired elements, a processor performing a program, or a combination thereof.

Internal to the controller 42A (Fig. 2), the process portion 112A (Fig. 2) is operatively connected 113A to the memory portion 114A. The process portion 112A is operatively connected 117A to the encrypt portion 116A. The memory portion 114A is operatively connected 115A to the encrypt portion 116A.

In response to pushbutton actuation, the process
portion 112A of the controller 42A generates/assembles
a message package containing information that is to be
transmitted. Preferably, data strings that represent
5   the information are retrieved from the memory
portion 114A of the controller 42A. The message
package information that is generated/assembled within
the controller 42A includes a start/wakeup instruction,
a security code, and at least one command that
10   represents the remote function request. The encrypt
portion 116A (Fig. 2) encrypts at least some of the
information that is to be transmitted to the device-
based transceiver (e.g., 30X, Fig. 1) in order to
prevent unauthorized interception and use. The
15   portions of the message information that are encrypted
preferably include the security code and the commands.
To further increase security, a sequence counter is
also part of the message information. The sequence
counter is changed (e.g., advanced) for each
20   transmission a portable transceiver makes to a device-
based transceiver. Encryption is also used to secure
the sequence counter during transmission.

The process portion 112A of the portable
transceiver controller 42A is operatively connected to

at least the following-mentioned elements, which are external to the controller. The process portion 112A of the controller 42A is operatively connected to the pushbutton switches 91A-95A. The process portion 112A

5 is operatively connected 43A to the display 82A. The process portion 112A also is operatively connected 45A to the RF transceive circuitry 44A. The process portion 112A receives operator input from the pushbutton switches 91A-95A, outputs messages to the

10 display 82A, and receives device-based transceiver messages from the RF transceive circuitry 44A. The process portion 112A also sends secure convenience function request messages to the RF transceive circuitry 44A for transmission to devices 35X and 35Y.

15 The device-based transceiver 30X illustrated in Fig. 3 in greater detail is an example of the configuration of the device-based transceivers 30X and 30Y (Fig 1). It is to be appreciated that the device-based transceiver 30Y may have similar

20 structure.

Turning to the controller 68X of device-based transceiver 30X illustrated in Fig. 3, the controller has at least three portions. A process portion 152X controls the controller 68X and processes information.

A memory portion 154X stores information. The memory

portion 154X is preferably an EEPROM, but can be any

non-volatile memory that can be programmed by the

circuitry within the device-based transceiver. A

5   decrypt portion 158X decrypts messages determined valid

by the process portion 152X. It is to be appreciated

that the functions performed within the blocks of the

controller part of the diagram shown in Fig. 3 may be

accomplished by discrete hard-wired elements, a

10   processor performing a program, or a combination

thereof.

Internal to the controller 68X, the process

portion 152X is operatively connected 153X to the

memory portion 154X. The process portion 152X is

15   operatively connected 157X to the decrypt portion 158X.

The memory portion 154X is operatively connected 155X

to the decrypt portion 158X.

The process portion 152X of the controller 68X is

operatively connected 33X to the device operations

20   system 38X of the device 35X. The process portion 152X

conveys a valid convenience request to the device

operations system 38X. The process portion 152X is

operatively connected to the RF transceive

circuitry 64X. The process portion 152X receives

convenience function request messages from the RF

transceive circuitry 64X. The process portion 152X

sends convenience function status messages to the RF

transceive circuitry 64X for transmission to the

5   portable transceiver that transmitted a function

request.

When a convenience function request signal is

received by the RF transceive circuitry 64X, the RF

transceive circuitry 64X communicates the message

10   packet contained in the signal to the process

portion 152X of the controller 68X. The process

portion 152X determines if the convenience function

request message is intended for its associated device

operations system 38X. If the process portion 152X

15   determines that the convenience function request

message is not intended for its associated device

operations system 38X, then the process portion goes

into sleep mode and the device-based transceiver awaits

another remote convenience function signal.

20   If the process portion 152X of the controller 68X

determines that the convenience function request

message is intended for its associated device

operations system 38X, then the decrypt portion 158X of

the controller 68X decrypts the encrypted portion of

the convenience function request message. The process
portion 152X then conveys the convenience function
request to its device operations system 38X.

Upon completion of the remotely requested

5   function, the device operations system 38X provides
status information to the process portion 152X. The
process portion 152X accesses the memory portion 154X
to retrieve appropriate information for the response or
acknowledgement. The stored information includes

10 stored messages used to respond/acknowledge, the
security code, etc. A status response message packet
is assembled within the process portion 152X and output
to the RF transceive circuitry 64X for transmission to
the portable transceiver that transmitted the enacted

15 convenience function request.

Turning now to the configuration of the portable
transceiver (e.g., 20A), configuration information 200
(Fig. 4) is stored in the memory (e.g., 114A) of each
portable transceiver in the arrangement 10. The

20 example of Fig. 4 illustrates the type of information
stored in memory, where the memory is preferably
EEPROM. The arrangement that uses the information
shown in Fig. 4 can support up to eight devices. As
noted earlier, any number of devices can be configured

into an arrangement up to the limit of what is

configurable. In one example, the limit is based on

the amount of memory available to store all of the

required information for each device and the maximum

5   number of communication channels in the arrangement.

The memory in each portable transceiver stores, as a

minimum, a portable transceiver serial number 210 and

an entity table 220.

Each portable transceiver has a distinctive serial

10   number 210 that is referred to by the variable name

FobID. (Portable transceivers are otherwise known as

fobs.) The FobID is programmed into the memory of a

portable transceiver at the time of manufacture.

The entity table stores access information for all

15   of the device-based transceivers the portable

transceiver is configured to access. The entity

table 220 illustrated in Fig. 4 has a maximum of eight

entities, or possible devices, it can configure. Each

entity in the entity table 220 has at least four types

20   of information associated with it: a device number 222,

referred to by the variable name DeviceID; an

encryption key 224, referred to by EncrptKey; a

sequence counter 226, referred to by SeqCnt; and a

communications channel 228, referred to by the variable name Channel.

The device number 222 (DeviceID) is an index number that represents a device's identification number within the arrangement which is set during configuration of the arrangement. The encryption key 224 (EncrptKey) is an encryption code for transmitting secure remote convenience messages to configured device-based transceivers. The encryption key for each entity in the entity table 220 of a portable transceiver is set at the time of manufacture. The sequence counter 226 (SeqCnt) is changed (e.g., advanced) for each transmission a portable transceiver makes to a device-based transceiver. The sequence counter 226 is set during configuration of the arrangement. The communications channel 228 (Channel) identifies the RF channel that communications will take place between the portable transceiver and each particular device in the entity table. The communications channel 228 (Channel) is set during configuration of the arrangement.

When the device mode pushbutton switch (e.g., 95A) is actuated on a portable transceiver (e.g., 20A) to select a particular device-based transceiver, the

device number 222 (DeviceID) of the device to be

controlled is retrieved from the memory portion of the

controller. The corresponding encryption key 224

(EncrptKey), sequence counter 226 (SeqCnt), and

5 communications channel 228 (Channel) are also retrieved

from memory. The retrieved information is used to

establish communications with the selected device-based

transceiver. Thus, each portable transceiver has

information stored in its entity table for each

10 device-based transceiver it is configured to

communicate with.

Turning now to the configuration of the device-

based transceiver (e.g., 30X, Fig. 1), configuration

information 300 (Fig. 5) is stored in the memory

15 (e.g., 154X) of each device-based transceiver in the

arrangement 10. The example of Fig. 5 illustrates the

type of information stored in memory, where the memory

is preferably EEPROM. The arrangement that uses the

information shown in Fig. 5 can support up to eight

20 portable transceivers. As noted earlier, any number of

portable transceivers can be configured into an

arrangement up to the limit of what is configurable.

That limit is based on the amount of memory available

to store all of the required information for each

portable transceiver and the maximum number of

communication channels capable of being used in the

arrangement. The memory in each device-based

transceiver stores, as a minimum, a device

5   identification number 310 (DeviceID), a communications

channel number 320 (Channel), and an entity table 330.

Each device-based transceiver is identified in an

arrangement by its DeviceID, which is programmed during

the configuration process. Each device-based

10   transceiver also has a fixed communications channel

number 320, designated by the variable Channel, stored

in its memory. The fixed communications channel

number 320 (Channel) matches the channel number stored

in the memory of the portable transceiver configured to

15   communicate with that device. The channel number 320

(Channel) is set during the configuration process.

Each device-based transceiver has information stored in

its entity table for each portable transceiver it is

configured to communicate with.

20   Each entity in the device-based transceiver entity

table corresponds to a single portable transceiver in

the arrangement the device-based transceiver is

configured to communicate with. Each entity in the

entity table 330 has at least three types of

information associated with it: a portable transceiver

serial number 332, referred to by the variable name

FobID; an encryption key 334, referred to by EncrptKey;

and a sequence counter 336, referred to by the variable

5   name SeqCnt.

Turning attention to Fig. 6, a portable

transceiver uses the method 500, as a minimum, to

transmit a convenience function to a device. In

step 510, an operator actuates the device mode

10   pushbutton switch to designate a device to control and,

consequently, a device-based transceiver to communicate

with. In step 520, the process portion of the portable

transceiver controller retrieves configuration

information for a device-based transceiver from the

15   entity table in the memory portion of the portable

transceiver controller. The configuration information

retrieved is based on the device-based transceiver the

operator selected by actuating the device mode

pushbutton switch.

20   In step 530, the operator actuates the appropriate

pushbutton to initiate convenience function activation.

In step 540, the process portion of the controller

generates a convenience function request message packet

based on the pushbutton switch actuation and the

information loaded from the memory. In step 550, the

encrypt portion of the controller encrypts at least

some of the convenience function request message. In

step 560, the RF circuitry in conjunction with the

5   antenna transmits the convenience function request

message on the communication channel specified by the

information retrieved from the entity table. Part of

the convenience function request message contains the

DeviceID and the FobID. The DeviceID is not encrypted

10   and a portion of the FobID is encrypted. All of the

devices in the communication range receive this

message.

Turning to Fig. 7, the device-based transceivers

use the method 600, as a minimum, to handle a

15   transmitted convenience function message. In step 610,

each device-based transceiver in the arrangement waits

in sleep mode until it receives a transmitted

convenience function message. In step 620, the device-

based transceiver determines if the unencrypted

20   DeviceID portion of the transmitted remote convenience

function request message matches the DeviceID stored in

its memory. If a device-based transceiver determines

that the DeviceID does not match (i.e., the

determination at step 620 is negative), then that

device-based transceiver waits in sleep mode (e.g.,

return to step 610) until it receives another remote

convenience function request message.

If a device-based transceiver determines that the

5   DeviceID does indeed match (i.e., the determination at

step 620 is affirmative), then the process proceeds to

step 630. At step 630, the device-based transceiver

determines if the unencrypted part of the FobID in the

transmitted remote convenience function request message

10   matches the FobID stored in its entity table in memory.

If the FobID does not match (i.e., the determination at

step 630 is negative), then that device-based

transceiver waits in sleep mode (e.g., return to

step 610) until it receives another remote convenience

15   function request message.

If the FobID does match (i.e., the determination

at step 630 is affirmative), then the process proceeds

to step 640. At step 640, the device-based transceiver

decrypts the remote convenience function request

20   message. At step 650, the device-based transceiver

conveys the convenience function request to the device

operations system of the associated device.

The process of configuring the arrangement sets

the memory portion of the controllers in both the

portable transceivers and the device-based transceivers. The variables mentioned above are set in the corresponding transceivers during the configuration process.

5   Illustrated in Fig. 8 is the same arrangement 10 shown in Fig. 1 but viewed with only the configuration information stored in the memory of each transceiver. Fig. 8 shows the configuration information for the arrangement 10 of three portable transceivers and two

10   device-based transceivers. The arrangement 10 can support up to 8 portable transceivers and 8 devices-based transceivers. An eight-element entity table in the memory of each portable transceiver represents eight possible devices the portable transceiver can

15   access. Each portable transceiver in Fig. 8 is configured to communicate with two different device-based transceivers. If a pushbutton switch is pressed on portable transceiver 20A (FobID A) to communicate with device-based transceiver 30Y (DeviceID =1), then

20   EncrptKey[1], SeqCnt[1], and Channel[1] will be loaded from portable transceiver memory to establish communications.

         A DeviceID is a unique number from 0 to 7 assigned to each device during the configuration process. Each

device-based transceiver stores information about each

portable transceiver it is configured to communicate

with. Likewise, an eight-element entity table in the

memory of each device-based transceiver represents

5   eight possible portable transceivers the device-based

transceiver can communicate with. Each device-based

transceiver in Fig. 8 is configured to communicate with

three different portable transceivers.

Thus, the configuration of arrangement 10 allows a

10   plurality of operators to control a plurality of

devices by using a plurality of portable transceivers

to communicate with a plurality of device-based

transceivers. The limit to the number of portable

transceivers communicating with device-based

15   transceivers in an arrangement is limited only by the

maximum number of transceivers, portable and device-

based, configurable by the arrangement. Each portable

transceiver can also control a plurality of types of

remotely controlled devices (e.g., vehicles, buildings,

20   etc.) as well as a plurality of functions at each

device. Although each portable transceiver must be

capable of communicating with each device-based

transceiver, the remote arrangement 10 can be

configured so that a particular portable transceiver

unit may remotely control the functions on some or all of the devices.

From the above description of the invention, those skilled in the art will perceive improvements, changes

5   and modifications. For example, the arrangement could be configured to operate without two-way communication between the portable transceiver and the device-based transceiver. Thus, the portable unit would be a transmitter unit, and the device-based unit would be

10   receiver units. Such improvements, changes and modifications within the skill of the art are intended to be covered by the appended claims.